



EKSELANS BY ITS

UNIVERSAL COAXIAL CABLE REMOTE CONTROL TRANSMITTER

IR RC · TRC · FA 505



- √ IR frequencies receiver
- √ Additional TRC may be installed in different rooms
- √ Voltage feeding via external PSU (FA 505) or coaxial line
- √ Remote control reception command by led blinking line
- √ Dynamic range >80dB
- √ Compatible with MD HD EASY RC



IR RC



TRC



FA 505



TECHNICAL TABLE

REFERENCE		IR RC
Code		124010
Infrared receiver (TRC) & Tx		
Infrared frequencies	KHz	38 - 56
RF frequencies	MHz	11
RCU command indication		LED
Voltage feeding	Vdc	5
Voltage feeding ports		DC Jack 3,5mm / ANT
Consumption	mA	<50
Infrared transmitter (RRC) & Rx		
Voltage feeding	Vdc	5
Voltage feeding ports		DC Jack 3,5mm
Consumption	mA	<50

REFERENCE		TRC
Code		125002
Infrared receiver (TRC)		
Infrared frequencies	KHz	38 - 56
RF frequencies	MHz	11
RCU command indication		LED
Voltage feeding	Vdc	5
Voltage feeding ports		DC Jack 3,5mm / ANT
Consumption	mA	<50

ACCESSORY

CODE	REFERENCE	DESCRIPTION
124007	FA 505	Power supply unit 5 Vdc / 500mA with USB output